



Wenzhou Safewire Electric Co.,Ltd.  
2nd floor, Wealth Garden, Liushi town, Yueqing, Wenzhou,China ,325604

Wenzhou Safewire Electric CO.,Ltd.

## SPECIFICATION SHEET

**PRODUCT NAME:** Access charger

**PRODUCT No. :** FT-12



Address:2nd floor, Wealth Garden, Liushi town, Yueqing, Wenzhou,China ,325604

Tel:0086-577-61725369

Mob:0086-18612380398

ZIP:325604

(E-mail) : [info@safewirele.com](mailto:info@safewirele.com)

(WEB): <http://www.safewirele.com>

**Tel:0086-18612380398;**

**Email:info@safewirele.com;**

**<http://www.safewirele.com>**

## 1) Product detail

1	Product Name	Accessed Wireless Charger
2	Item No.	FT-12
3	Materials	ABS
4	Rate of work	5W 7.5W 10W
5	Input	5V/2A 9V/1.67A
6	Output	5V/1A 9V/1A
7	Charging Distance	2-8mm
8	Voltage	110-240V
9	Color	White
10	Certification	CE,FCC,RoHS
11	Product size	dia. 95mm
12	Product hight	30mm
13	Hole size	dia.85mm
14	Wire length	1.2m / 1.8m / 2m
15	Charge efficiency	>75%
16	Product weight	120g

## Feature

1. Access flush-mounting :30mm recessed height ,Smart and convenient charging.  
Wireless charger : Any other Qi charger-supported device!
2. Dynamic power adjustment, ensure the versatility of the adapter.
3. Over voltage, over current, short circuit and other perfect protection functions.
4. **Application** : coffee shop, western restaurant, bar, airport, high-speed railway, desk and other public places.

## Product show



## **Remark:**

- 1.Do not use the charger near water,liquid or wet areas.Clean using a soft paper or towel.
- 2.Do not put any dangerous articles on this charger.
- 3.Cut off the power before cleaning the charger.
- 4.Do not try to disassemble,repair or remould the product by yourself.
- 5.Unplua this device when unused for long periods of time.
- 6.Do not expose your charger to temperature above 45°C.Keep out of direct sunlight.

## **Application:**



hotel

Emergency control center

office